



0.7 dB NF Low Noise Amplifier, Operating from 700 MHz to 2.7 GHz with 23 dB Gain, 21 dBm Psat and SMA

TECHNICAL DATA SHEET

PE15A1067

The PE15A1067 is a low noise coaxial amplifier operating in the 700 MHz to 2700 MHz frequency range. Impressive broadband typical performance includes 0.7 dB noise figure, 23 dB small signal gain, +18 dBm P1dB, and an output 3rd order intercept point of +35 dBm. This exceptional technical performance is achieved through the use of a hybrid MIC design and advanced E-pHEMT devices. The low noise amplifier requires a +12V DC power supply, and operates over a temperature range of -40°C to +85°C. The rugged and compact package supports SMA Female connectors and RFI and Ground pins. And for highly reliable operation, the model is guaranteed to meet MIL-STD-202 environmental test conditions for Humidity, Shock, Vibration, and Altitude.

Features

- 700 MHz to 2700 MHz Frequency Range
- Low Noise Figure: 0.7 dB
- High Dynamic Range
- Efficient GaAs pHEMT Design
- Small Signal Gain: 23 dB
- Output P1dB: +18 dBm
- Output IP3: +35 dBm
- Operating Temperature: -40°C to +85°C
- 50 Ohm Input and Output Matched
- DC Power Supply: +12V / 65 mA
- SMA Female Connectors
- Designed to meet MIL-STD-202 Test Conditions

Applications

- Test & Measurement
- R&D Labs
- General Purpose Amplification
- Aerospace & Defense
- Wireless Infrastructure
- Communication Systems

Electrical Specifications (TA = +25°C, DC Voltage = +12Vdc, DC Current = 65mA)

Description	Minimum	Typical	Maximum	Units
Frequency Range	0.7		2.7	GHz
Small Signal Gain	19	23		dB
Gain Flatness		±1	±1.5	dB
Gain Variation Over Temperature		0.014		dB/°C
Output at 1 dB Compression Point	+18	+18		dBm
Saturated Output Power (Psat)	+19	+21		dBm
Output 3rd Intercept Point	+33	+35		dBm
Noise Figure		0.7	0.9	dB
Input VSWR		1.7:1	2.5:1	
Output VSWR		1.2:1	2:1	
Reverse Isolation		-33		dB
Operating DC Voltage	+9	+12	+15	Volts
Operating DC Current		65	75	mA
Operating Temperature Range	-40		+85	°C

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [0.7 dB NF Low Noise Amplifier, Operating from 700 MHz to 2.7 GHz with 23 dB Gain, 21 dBm Psat and SMA PE15A1067](#)



0.7 dB NF Low Noise Amplifier, Operating from 700 MHz
to 2.7 GHz with 23 dB Gain, 21 dBm Psat and SMA

TECHNICAL DATA SHEET

PE15A1067

Absolute Maximum Rating

Parameter	Rating	Units
Supply Voltage	+16	V
RF Input Power	+27	dBm
Operating Temperature	-40 to +85	°C
Storage Temperature	-55 to +125	°C



ESD Sensitive Material,
Transport material in
Approved ESD bags.
Handle only in approved
ESD Workstation.

Mechanical Specifications

Size

Length	1 in [25.4 mm]
Width	0.79 in [20.07 mm]
Height	0.45 in [11.43 mm]
Input Connector	SMA Female
Output Connector	SMA Female

Environmental Specifications

Temperature

Operating Range	-40 to +85 deg C
Storage Range	-55 to +125 deg C

Humidity	MIL-STD-202F, Method 103B, Condition B
Shock	MIL-STD-202F, Method 213B, Condition B
Vibration	MIL-STD-202F, Method 204D, Condition B
Altitude	MIL-STD-202F, Method 105C, Condition B

Compliance Certifications (see [product page](#) for current document)

Plotted and Other Data

Notes:

- Values at +25 °C, sea level
- ESD Sensitive Material, Transport material in Approved ESD bags. Handle only in approved ESD Workstation.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [0.7 dB NF Low Noise Amplifier, Operating from 700 MHz to 2.7 GHz with 23 dB Gain, 21 dBm Psat and SMA PE15A1067](#)




0.7 dB NF Low Noise Amplifier, Operating from 700 MHz to 2.7 GHz with 23 dB Gain, 21 dBm Psat and SMA

TECHNICAL DATA SHEET

PE15A1067

Typical Performance Data




Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [0.7 dB NF Low Noise Amplifier, Operating from 700 MHz to 2.7 GHz with 23 dB Gain, 21 dBm Psat and SMA PE15A1067](#)



0.7 dB NF Low Noise Amplifier, Operating from 700 MHz to 2.7 GHz with 23 dB Gain, 21 dBm Psat and SMA

TECHNICAL DATA SHEET

PE15A1067




Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [0.7 dB NF Low Noise Amplifier, Operating from 700 MHz to 2.7 GHz with 23 dB Gain, 21 dBm Psat and SMA PE15A1067](#)



0.7 dB NF Low Noise Amplifier, Operating from 700 MHz to 2.7 GHz with 23 dB Gain, 21 dBm Psat and SMA

TECHNICAL DATA SHEET

PE15A1067



Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [0.7 dB NF Low Noise Amplifier, Operating from 700 MHz to 2.7 GHz with 23 dB Gain, 21 dBm Psat and SMA PE15A1067](#)



0.7 dB NF Low Noise Amplifier, Operating from 700 MHz
to 2.7 GHz with 23 dB Gain, 21 dBm Psat and SMA

TECHNICAL DATA SHEET

PE15A1067

0.7 dB NF Low Noise Amplifier, Operating from 700 MHz to 2.7 GHz with 23 dB Gain, 21 dBm Psat and SMA from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry.


Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [0.7 dB NF Low Noise Amplifier, Operating from 700 MHz to 2.7 GHz with 23 dB Gain, 21 dBm Psat and SMA PE15A1067](https://www.pasternack.com/0.7-db-2.7-ghz-low-noise-amplifier-23-db-gain-sma-pe15a1067-p.aspx)

URL: <https://www.pasternack.com/0.7-db-2.7-ghz-low-noise-amplifier-23-db-gain-sma-pe15a1067-p.aspx>

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

PE15A1067 CAD Drawing

0.7 dB NF Low Noise Amplifier, Operating from 700 MHz to 2.7 GHz with 23 dB Gain, 21 dBm Psat and SMA



NOTES:
1. UNLESS OTHERWISE SPECIFIED ALL DIMENSIONS ARE NOMINAL.
2. ALL SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE AT ANY TIME.
3. DIMENSIONS ARE IN INCHES [mm].

DWG TITLE
PE15A1067

PE PASTERNAK®
THE ENGINEER'S RF SOURCE
Pasternack Enterprises, Inc.
P.O. Box 16759 | Irvine | CA | 92623
Phone: (949) 261-1920 | Fax: (949) 261-7451
Website: www.pasternack.com | E-Mail: sales@pasternack.com

CAGE CODE 53919

SIZE A

SCALE N/A

CAD FILE 04/23/18

7361