



6 GHz to 12 GHz, Gain Block Amplifier, 12 dB
 Gain, 20 dBm IP3, 2.3 dB NF, SMA

TECHNICAL DATA SHEET **PE15A8006**

The PE15A8006 is wideband general purpose RF coaxial gain block amplifier operating in the 6 GHz to 12 GHz frequency range. The amplifier offers 10 dBm min of P1dB, 12 dB typ of Gain, OIP3 typ of 20 dBm. This exceptional technical performance is achieved through the use of hybrid MIC design and advanced GaAs PHEMT devices. Input/output ports are matched for 50 ohms and are AC coupled. This gain block amplifier requires only a single positive supply, typically a +12V DC power supply and includes built-in voltage regulation, is unconditionally stable and operates over the temperature range of -30°C and +70°C.

Features

- 6 GHz to 12 GHz Frequency Range
- P1dB: 10 dBm
- Small Signal Gain: 12 dB
- OIP3: 20 dBm
- 50 Ohm Input and Output Matched
- -30 to +70°C Operating Temperature
- Unconditionally Stable
- Single DC Positive Supply
- Built-in Voltage Regulator

Applications

- Laboratory Applications
- R&D Labs
- Military Radio
- Radar Systems
- Telecom Infrastructure
- Test Instrumentation
- Military & Space
- Communication Systems
- Wireless Communication
- Microwave Radio Systems
- Cellular Base Stations
- Low Noise Amplifier
- General Purpose Amplification
- General Purpose Wireless
- Wideband Gain Block
- IF Amplifier/RF Driver Amplifier
- RF Wideband Front Ends
- RF Pre-amplification

Electrical Specifications (TA = +25°C, DC Voltage = 12Volts, DC Current = 80mA)

Description	Minimum	Typical	Maximum	Units
Frequency Range	6		12	GHz
Small Signal Gain	11	12		dB
Gain Flatness		±0.4		dB
Output at 1 dB Compression Point	+10			dBm
Output 3rd Intercept Point		+20		dBm
Noise Figure		2.3		dB
Input VSWR			2:1	
Output VSWR			2:1	
Operating DC Voltage	11	12	15	Volts
Operating DC Current		80		mA
Operating Temperature Range	-30		+70	°C

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [6 GHz to 12 GHz, Gain Block Amplifier, 12 dB Gain, 20 dBm IP3, 2.3 dB NF, SMA PE15A8006](#)



6 GHz to 12 GHz, Gain Block Amplifier, 12 dB
Gain, 20 dBm IP3, 2.3 dB NF, SMA

TECHNICAL DATA SHEET

PE15A8006


Compliance Certifications (see [product page](#) for current document)

Plotted and Other Data

Notes:

- Values at +25 °C, sea level
- ESD Sensitive Material, Transport material in Approved ESD bags. Handle only in approved ESD Workstation.

Typical Performance Data




Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [6 GHz to 12 GHz, Gain Block Amplifier, 12 dB Gain, 20 dBm IP3, 2.3 dB NF, SMA PE15A8006](#)



6 GHz to 12 GHz, Gain Block Amplifier, 12 dB
Gain, 20 dBm IP3, 2.3 dB NF, SMA

TECHNICAL DATA SHEET

PE15A8006




Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [6 GHz to 12 GHz, Gain Block Amplifier, 12 dB Gain, 20 dBm IP3, 2.3 dB NF, SMA PE15A8006](#)



6 GHz to 12 GHz, Gain Block Amplifier, 12 dB
Gain, 20 dBm IP3, 2.3 dB NF, SMA

TECHNICAL DATA SHEET

PE15A8006



6 GHz to 12 GHz, Gain Block Amplifier, 12 dB Gain, 20 dBm IP3, 2.3 dB NF, SMA from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99% availability and are part of the broadest selection in the industry.


Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [6 GHz to 12 GHz, Gain Block Amplifier, 12 dB Gain, 20 dBm IP3, 2.3 dB NF, SMA PE15A8006](https://www.pasternack.com/12-ghz-gain-block-amplifier-12-db-gain-20-dbm-ip3-2.3-db-nf-sma-pe15a8006)

URL: <https://www.pasternack.com/12-ghz-gain-block-amplifier-12-db-gain-2.3-db-sma-pe15a8006-p.aspx>

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

PE15A8006 CAD Drawing

6 GHz to 12 GHz, Gain Block Amplifier, 12 dB Gain, 20 dBm IP3, 2.3 dB NF, SMA



NOTES:
 1. UNLESS OTHERWISE SPECIFIED ALL DIMENSIONS ARE NOMINAL.
 2. ALL SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE AT ANY TIME.
 3. DIMENSIONS ARE IN INCHES [mm].

DWG TITLE
PE15A8006

FSCM NO. 53919

CAD FILE 032116

SCALE N/A

SIZE A

2233

PE PASTERNAK
 THE ENGINEERS' RF SOURCE
 Pasternack Enterprises, Inc.
 P.O. Box 16759 | Irvine | CA | 92623
 Phone: (949) 261-1920 | Fax: (949) 261-7451
 Website: www.pasternack.com | E-Mail: sales@pasternack.com