



Slide-On BMA Jack 2 Hole Flange to SMA Male  
Cable 150 cm Length Using RG402 Coax

RF Cable Assemblies Technical Data Sheet

PE3W06981-150CM

### Configuration

- Connector 1: Slide-OnBMA Jack 2 Hole Flange
- Connector 2: SMA Male
- Cable Type: RG402

### Features

- Max Frequency 18 GHz
- 69.5% Phase Velocity

### Applications

- General Purpose
- Laboratory Use

### Description

Pasternack's PE3W06981-150CM BMA jack slide-on 2 hole flange to SMA male 150 cm cable using RG402 coax is part of our full line of RF components available for same-day shipping. Pasternack's semi-rigid RF cable assemblies are ideal for high performance applications and can be formed, using proper tooling, to the routing pattern required. This Pasternack BMA to SMA cable assembly has a jack to male gender configuration with 50 ohm semi-rigid RG402 coax. The PE3W06981-150CM BMA jack to SMA male cable assembly operates to 18 GHz. Our RF cable assembly with BMA 2 hole flange interface allows designers to create external connections on their product enclosures, and can be used in a variety of other rack mount and panel mount applications.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other available RF cable assembly value added services include connector orientation or clocking, heat shrink booting and custom labeling. RF testing can also be performed to document the electrical performance of your cable assembly.

### Electrical Specifications

| Description             | Minimum | Typical | Maximum | Units |
|-------------------------|---------|---------|---------|-------|
| Frequency Range         | DC      |         | 18      | GHz   |
| VSWR                    |         |         | 1.5:1   |       |
| Velocity of Propagation |         | 69.5    |         | %     |

### Specifications by Frequency

| Description           | F1   | F2   | F3   | F4   | F5  | Units |
|-----------------------|------|------|------|------|-----|-------|
| Frequency             | 1    | 2    | 4.5  | 9    | 18  | GHz   |
| Insertion Loss (Max.) | 0.79 | 0.97 | 1.42 | 2.24 | 3.4 | dB    |

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [Slide-On BMA Jack 2 Hole Flange to SMA Male Cable 150 cm Length Using RG402 Coax PE3W06981-150CM](#)



## Slide-On BMA Jack 2 Hole Flange to SMA Male Cable 150 cm Length Using RG402 Coax

### RF Cable Assemblies Technical Data Sheet

PE3W06981-150CM

#### Electrical Specification Notes:

The Insertion Loss data above is based on the performance specifications of the coax used in this assembly. The Insertion Loss includes an estimated insertion loss of 0.2dB of connector loss.

#### Mechanical Specifications

##### Cable Assembly

|          |                      |
|----------|----------------------|
| Length*  | 59.05 in [149.99 cm] |
| Diameter | 0.74 in [18.8 mm]    |

##### Cable

|                                      |                           |
|--------------------------------------|---------------------------|
| Cable Type                           | RG402                     |
| Impedance                            | 50 Ohms                   |
| Inner Conductor Type                 | Solid                     |
| Inner Conductor Material and Plating | Copper Clad Steel, Silver |
| Dielectric Type                      | PTFE                      |
| Number of Shields                    | 1                         |
| Outer Conductor Material and Plating | Copper                    |

|                              |                   |
|------------------------------|-------------------|
| Repeated Minimum Bend Radius | 0.25 in [6.35 mm] |
|------------------------------|-------------------|

#### Connectors

| Description                          | Connector 1            | Connector 2                |
|--------------------------------------|------------------------|----------------------------|
| Type                                 | BMA Jack 2 Hole Flange | SMA Male                   |
| Impedance                            | 50 Ohms                | 50 Ohms                    |
| Connection Method                    | Slide-On               |                            |
| Mating Cycles                        | 1,000                  |                            |
| Contact Material and Plating         | Beryllium Copper, Gold |                            |
| Contact Plating Specification        | 51.18µ in. minimum     |                            |
| Dielectric Type                      | PTFE                   |                            |
| Outer Conductor Material and Plating | Beryllium Copper, Gold |                            |
| Body Material and Plating            | Stainless Steel, Gold  | Brass, Gold over Nickel    |
| Body Plating Specification           | 19.68µ in. minimum     |                            |
| Coupling Nut Material and Plating    |                        | Passivated Stainless Steel |
| Hex Size                             |                        | 5/16 inch                  |
| Torque                               |                        | 8 in-lbs [0.9 Nm]          |

#### Mechanical Specification Notes:

\*All cable assemblies have a length tolerance of 1.5% or  $\pm 3/8"$ , whichever is greater.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [Slide-On BMA Jack 2 Hole Flange to SMA Male Cable 150 cm Length Using RG402 Coax PE3W06981-150CM](#)



Slide-On BMA Jack 2 Hole Flange to SMA Male  
Cable 150 cm Length Using RG402 Coax

RF Cable Assemblies Technical Data Sheet

PE3W06981-150CM

**Compliance Certifications** (see [product page](#) for current document)

**Plotted and Other Data**

Notes:

**How to Order**

Part Number Configuration:

**PE3W06981**

**- xx**

**uu**

Unit of Measure:  
cm = Centimeters  
<blank> = Inches  
Length  
Base Number

Example: PE3W06981-12 = 12 inches long cable  
PE3W06981-100cm = 100 cm long cable

Slide-On BMA Jack 2 Hole Flange to SMA Male Cable 150 cm Length Using RG402 Coax from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [Slide-On BMA Jack 2 Hole Flange to SMA Male Cable 150 cm Length Using RG402 Coax PE3W06981-150CM](#)

URL: <https://www.pasternack.com/bma-jack-sma-male-rg402u-cable-assembly-pe3w06981-150cm-p.aspx>

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

# PE3W06981-150CM CAD Drawing

Slide-On BMA Jack 2 Hole Flange to SMA Male Cable 150 cm Length Using RG402 Coax

