



RF Cable Assemblies Technical Data Sheet

PE3W07080/HS-36


Configuration

Connector 1: BNC MaleConnector 2: FAKRA Jack

• Cable Type: RG316

Features

- Max Frequency 3 GHz
- 69% Phase Velocity
- FEP Jacket



Applications

· General Purpose

· Laboratory Use

Description

Pasternack's PE3W07080/HS-36 BNC male to water blue FAKRA jack 36 inch cable using RG316 coax is part of our full line of RF components available for same-day shipping. Pasternack's flexible RF cable assemblies are ideal for applications where tight bends and flexure are required. This Pasternack BNC to FAKRA cable assembly has a male to jack gender configuration with 50 ohm flexible RG316 coax. The PE3W07080/HS-36 BNC male to FAKRA jack cable assembly operates to 3 GHz.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other available RF cable assembly value added services include connector orientation or clocking, heat shrink booting and custom labeling. RF testing can also be performed to document the electrical performance of your cable assembly.

Electrical Specifications

| Description | Minimum | Typical | Maximum | Units |
|--------------------------------------|---------|--------------|---------|--------------|
| Frequency Range | DC | | 3 | GHz |
| VSWR | | | 1.5:1 | |
| Velocity of Propagation | | 69 | | % |
| Capacitance | | 29.4 [96.46] | | pF/ft [pF/m] |
| Operating Voltage (AC) | | | 335 | Vrms |
| Dielectric Withstanding Voltage (AC) | | | 1,000 | Vrms |
| Jacket Spark | | | 2,000 | Vrms |

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: BNC Male to Water Blue FAKRA Jack Cable 36 Inch Length Using RG316 Coax with Heat-Shrink PE3W07080/HS-36





RF Cable Assemblies Technical Data Sheet

PE3W07080/HS-36

Specifications by Frequency

| Description | F1 | F2 | F3 | F4 | F5 | Units |
|-----------------------|------|------|------|-----|------|-------|
| Frequency | 0.25 | 0.5 | 1 | 2.5 | 3 | GHz |
| Insertion Loss (Max.) | 0.61 | 0.73 | 1.34 | 1.7 | 1.94 | dB |

Electrical Specification Notes:

The Insertion Loss data above is based on the performance specifications of the coax use in this assembly. The Insertion Loss includes an estimated insertion loss of 0.2dB of connector Loss

Mechanical Specifications

Cable Assembly

Length* 36 in [914.4 mm]
Diameter 0.57 in [14.48 mm]

Cable

Cable Type
Impedance
Inner Conductor Type

Inner Conductor Material and Plating

Dielectric Type Number of Shields Shield Layer 1 Jacket Material Jacket Diameter RG316 50 Ohms Stranded

Copper Clad Steel, Silver

PTFE 1

Silver Plated Copper Braid

FEP, Tan

0.102 in [2.59 mm]

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: BNC Male to Water Blue FAKRA Jack Cable 36 Inch Length Using RG316 Coax with Heat-Shrink PE3W07080/HS-36





RF Cable Assemblies Technical Data Sheet

PE3W07080/HS-36

Connectors

| Description | Connector 1 | Connector 2 FAKRA Jack | |
|--------------------------------------|-----------------|-------------------------|--|
| Туре | BNC Male | | |
| Specification | MIL-STD-348A | | |
| Impedance | 50 Ohms | 50 Ohms | |
| Configuration | Straight | Straight | |
| Mating Cycles | 500 | | |
| Contact Material and Plating | Brass, Gold | Phosphor Bronze, Gold | |
| Contact Plating Specification | 30 µin minimum | | |
| Dielectric Type | PTFE | PTFE | |
| Outer Conductor Material and Plating | | Brass, Nickel | |
| Body Material and Plating | Brass, Nickel | Plastic | |
| Body Plating Specification | 100 μin minimum | | |
| Coupling Nut Material and Plating | Brass, Nickel | | |

Mechanical Specification Notes:

Environmental Specifications

Temperature

Operating Range -40 to +85 deg C

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: BNC Male to Water Blue FAKRA Jack Cable 36 Inch Length Using RG316 Coax with Heat-Shrink PE3W07080/HS-36

^{*}All cable assemblies have a length tolerance of 1.5% or \pm 3/8", whichever is greater.





RF Cable Assemblies Technical Data Sheet

PE3W07080/HS-36

How to Order

Part Number Configuration:

PE3W07080/HS - xx uu

Unit of Measure:
cm = Centimeters

Length
Base Number

Example: PE3W07080/HS-12 = 12 inches long cable PE3W07080/HS-100cm = 100 cm long cable

BNC Male to Water Blue FAKRA Jack Cable 36 Inch Length Using RG316 Coax with HeatShrink from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: BNC Male to Water Blue FAKRA Jack Cable 36 Inch Length Using RG316 Coax with HeatShrink PE3W07080/HS-36

URL: https://www.pasternack.com/bnc-male-fakra-jack-rg316u-cable-assembly-pe3w07080-hs-36-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

PE3W07080/HS-36 CAD Drawing BNC Male to Water Blue FAKRA Jack Cable 36 Inch Length Using RG316 Coax with HeatShrink

