

DC Block on Inner Conductor BNC Male to BNC Female Operating From 10 MHz to 4 GHz



DC Blocks Technical Data Sheet

PE8216

Features

- Inner DC Block
- Operates from 10 MHz to 4 GHz

Applications

- Test & Measurement
- Ground Loop Elimination
- Signal to Noise Ratio (SNR) Improvement

Good Insertion Loss of 0.5 dB Max

Description

Pasternack's PE8216 is an inner DC block with BNC connectors. It has a blocking capacitor on the inner conductor and operates from 10 MHz to 4 GHz. Our BNC DC block offers good insertion loss of 0.5 dB and has a maximum operating voltage of 200 Vdc. DC blocks are commonly used to filter out unwanted DC signals, while allowing AC drive signals to pass through. They can help improve signal to noise ratio (SNR), eliminate ground loops, or provide isolation in your test setup. All of Pasternack's DC blocks are in stock and available to ship same-day.

Electrical Specifications

Description	Minimum	Typical	Maximum	Units
Frequency Range	0.01		4	GHz
Impedance		50		Ohms
VSWR			1.35:1	
Insertion Loss			0.5	dB
Operating Voltage (DC)			200	Volts

Mechanical Specifications

Size Length Width	1.6 in [40.64 mm] 0.57 in [14.48 mm]
Weight	0.053 lbs [24.04 g]
Housing Material and Plating	Brass, Nickel
Configuration Design Package Type	Inner DC Block Connectorized

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: DC Block on Inner Conductor BNC Male to BNC Female Operating From 10 MHz to 4 GHz PE8216

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com





DC Block on Inner Conductor BNC Male to BNC Female Operating From 10 MHz to 4 GHz



PE8216

DC Blocks Technical Data Sheet

Description	Connector 1	Connector 2	
Туре	BNC Male	BNC Female	
Connector Specification	MIL-STD-348 MIL-STD-348		
Inner Conductor Material and Plating	Beryllium Copper, Gold	Beryllium Copper, Gold	
Coupling Nut Material and Plating	Brass, Nickel		
Body Material and Plating	Brass, Nickel	Brass, Nickel	
Operating Range	-65 to +125 deg C		
Operating Kange	-65 to +125 deg C		
ompliance Certifications (see product p	bage for current document)		
otted and Other Data Notes:			

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: DC Block on Inner Conductor BNC Male to BNC Female Operating From 10 MHz to 4 GHz PE8216

same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99%

URL: https://www.pasternack.com/50-ohm-bnc-inner-dc-block-0.1-4-ghz-pe8216-p.aspx

availability and are part of the broadest selection in the industry.

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451

ISO 9001 : 2008 Registered



Sales@Pasternack.com • Techsupport@Pasternack.com

PE8216 CAD Drawing DC Block on Inner Conductor BNC Male to BNC Female Operating From 10 MHz to 4 GHz

