



WR-102 UG-1493/U Square Cover Flange
to SMA Female Waveguide to Coax Adapter
Operating From 7 GHz to 11 GHz, X Band

Waveguide to Coax Adapters Technical Data Sheet

PE9805

Features

- X Band, 7 to 11 GHz Frequency Range
- WR-102 Waveguide Interface with UG-1493/U Square Cover Flange
- SMA Female Coaxial Interface
- Comprehensive waveguide offerings also include E-Bends, H-Bends, Sections, Filters, Terminations, Couplers, and more.

Description

The PE9805 is a waveguide to coaxial adapter operating in the X band with a 7 to 11 GHz frequency range. This adapter offers a WR-102 waveguide interface size coupled with a precision tolerance UG-1493/U square cover flange. The PE9805 is constructed of aluminum to ensure durability and repeatable RF performance. The SMA female connector mates with commercially available 2.92mm and 3.5mm connectors. The package is REACH and RoHS compliant.

Configuration

Waveguide Size	WR-102
Flange	UG-1493/U Square Cover
RF Connector	SMA Female
Impedance	50 Ohms
Body Geometry	Right Angle

Electrical Specifications

Description	Minimum	Typical	Maximum	Units
Frequency Range	7		11	GHz
VSWR			1.25:1	

Mechanical Specifications

Size	
Length	1.13 in [28.7 mm]
Width	1.69 in [42.93 mm]
Height	1.69 in [42.93 mm]
Weight	0.149 lbs [67.59 g]

RF Connector

Connector Type	SMA Female
Body Material and Plating	Stainless Steel

Waveguide Interface

Waveguide Type	WR-102
Flange Type	Square Cover
Flange Designation	UG-1493/U
Body Material and Plating	Aluminum

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [WR-102 UG-1493/U Square Cover Flange to SMA Female Waveguide to Coax Adapter Operating From 7 GHz to 11 GHz, X Band PE9805](#)



WR-102 UG-1493/U Square Cover Flange
to SMA Female Waveguide to Coax Adapter
Operating From 7 GHz to 11 GHz, X Band

Waveguide to Coax Adapters Technical Data Sheet

PE9805


Compliance Certifications (see [product page](#) for current document)

Plotted and Other Data

Notes:

- Values at +25 °C, sea level unless stated otherwise

Typical Performance Data



Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [WR-102 UG-1493/U Square Cover Flange to SMA Female Waveguide to Coax Adapter Operating From 7 GHz to 11 GHz, X Band PE9805](#)



WR-102 UG-1493/U Square Cover Flange
to SMA Female Waveguide to Coax Adapter
Operating From 7 GHz to 11 GHz, X Band

Waveguide to Coax Adapters Technical Data Sheet

PE9805

WR-102 UG-1493/U Square Cover Flange to SMA Female Waveguide to Coax Adapter Operating From 7 GHz to 11 GHz, X Band from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry.


Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [WR-102 UG-1493/U Square Cover Flange to SMA Female Waveguide to Coax Adapter Operating From 7 GHz to 11 GHz, X Band PE9805](https://www.pasternack.com/waveguide-to-sma-type-female-frequency-range-700-1100-ghz-pe9805-p.aspx)

URL: <https://www.pasternack.com/waveguide-to-sma-type-female-frequency-range-700-1100-ghz-pe9805-p.aspx>

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

PE9805 CAD Drawing

WR-102 UG-1493/U Square Cover Flange to SMA Female Waveguide
to Coax Adapter Operating From 7 GHz to 11 GHz, X Band



STANDARD TOLERANCES

.XX ±0.02
.XXX ±0.01

*STANDARD TOLERANCES APPLY
ONLY TO DIMENSIONS IN INCHES

PE PASTERNAK
THE ENGINEER'S RF SOURCE

Pasternack Enterprises, Inc.
P.O. Box 16759 | Irvine | CA | 92623
Phone: (949) 261-1920 | Fax: (949) 261-7451
Website: www.pasternack.com | E-Mail: sales@pasternack.com

DWG TITLE

PE9805

NOTES:
1. UNLESS OTHERWISE SPECIFIED ALL DIMENSIONS ARE NOMINAL.
2. ALL SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE AT ANY TIME.
3. DIMENSIONS ARE IN INCHES [mm].

CAGE CODE 53919

CAD FILE 050517

SCALE N/A

SIZE A

2233