



WR-34 UG-1530/U Square Cover Flange to 2.92mm Female Waveguide to Coax Adapter Operating From 22 GHz to 33 GHz

Waveguide to Coax Adapters Technical Data Sheet

PEWCA1001

Features

- 22 to 33 GHz Frequency Range
- WR-34 Waveguide Interface

UG-1530/U Square Cover Flange2.92mm Female RF Interface

- Applications
 - Test Benches
 - Radar

- Satellite
- Microwave Radio Systems
- Military and Space
- Communication Systems

Description

The PEWCA1001 is a waveguide to coaxial adapter operating in the 22 to 33 GHz frequency range. This adapter offers a WR-34 waveguide interface size using a standard Square Cover Flange. The PEWCA1001 is constructed of Copper Alloy and painted to ensure durability. The coaxial connector offered by this adapter uses a 2.92mm Female Nickel Plated Brass Connector.

Configuration

Waveguide Size Flange

RF Connector

Impedance

Body Geometry

WR-34

UG-1530/U Square Cover

2.92mm Female

50 Ohms Right Angle

Electrical Specifications

Description	Minimum	Typical	Maximum	Units
Frequency Range	22		33	GHz
VSWR		1.25:1		

Mechanical Specifications

Weight 0.078 lbs [35.38 g]

RF Connector

Connector Type 2.92mm Female Body Material and Plating Brass, Nickel

Waveguide Interface

Waveguide Type WR-34
Flange Type Square Cover
Flange Designation UG-1530/U
Body Material and Plating Copper Alloy, Paint

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: WR-34 UG-1530/U Square Cover Flange to 2.92mm Female Waveguide to Coax Adapter Operating From 22 GHz to 33 GHz PEWCA1001

ISO 9001 : 2008 Registered



WR-34 UG-1530/U Square Cover Flange to 2.92mm Female Waveguide to Coax Adapter Operating From 22 GHz to 33 GHz



Waveguide to Coax Adapters Technical Data Sheet

PEWCA1001

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

• Values at +25 °C, sea level unless stated otherwise

Typical Performance Data



WR-34 UG-1530/U Square Cover Flange to 2.92mm Female Waveguide to Coax Adapter Operating From 22 GHz to 33 GHz from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: WR-34 UG-1530/U Square Cover Flange to 2.92mm Female Waveguide to Coax Adapter Operating From 22 GHz to 33 GHz PEWCA1001

https://www.pasternack.com/wr-34-ug1530-square-2.92mm-female-waveguide-coax-adapter-33-ghz-pewca1001-p. URL: aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.



PEWCA1001 CAD Drawing

WR-34 UG-1530/U Square Cover Flange to 2.92mm Female Waveguide to Coax Adapter Operating From 22 GHz to 33 GHz

