

WR-62 UG-1665/U Square Cover Flange to SMA Female Waveguide to Coax Adapter Operating From 12.4 GHz to 18 GHz, Ku Band



PEWCA1023

Waveguide to Coax Adapters Technical Data Sheet

Features

- Ku Band 12.4 to 18 GHz Frequency Range
- WR-62 Waveguide Interface with UG-1665/U Square Cover Flange
- SMA Female RF Interface

Applications

- Test Benches
- Radar

- Satellite
- Microwave Radio Systems
- Military and Space

Comprehensive waveguide offerings also include

E-Bends, H-Bends, Sections, Filters, Terminations,

Communication Systems

Description

The PEWCA1023 is a waveguide to coaxial adapter operating in the Ku Band with a 12.4 to 18 GHz frequency range. This adapter offers a WR-62 waveguide interface size coupled with a precision tolerance UG-1665/U Square Cover flange. The PEWCA1023 is constructed of aluminum to ensure durability and repeatable RF performance. The coaxial connection offered by this adapter uses a SMA Female connector.

Configuration

Waveguide Size Flange RF Connector Body Geometry WR-62 UG-1665/U Square Cover SMA Female Right Angle

Couplers, and more.

Electrical Specifications

Description	Minimum	Typical	Maximum	Units
Frequency Range	12.4		18	GHz
VSWR			1.25:1	
Insertion Loss		0.3		dB

Mechanical Specifications

RF Connector

Connector Type

Waveguide Interface

Waveguide Type Flange Type Flange Designation Body Material and Plating

SMA Female

WR-62 Square Cover UG-1665/U Aluminum, Chem Film

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: WR-62 UG-1665/U Square Cover Flange to SMA Female Waveguide to Coax Adapter Operating From 12.4 GHz to 18 GHz, Ku Band PEWCA1023

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com



WR-62 UG-1665/U Square Cover Flange to SMA Female Waveguide to Coax Adapter Operating From 12.4 GHz to 18 GHz, Ku Band



Compliance Certifications (see product page for current document)

Plotted and Other Data Notes:

• Values at +25 °C, sea level unless stated otherwise

Typical Performance Data



WR-62 UG-1665/U Square Cover Flange to SMA Female Waveguide to Coax Adapter Operating From 12.4 GHz to 18 GHz, Ku Band from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: WR-62 UG-1665/U Square Cover Flange to SMA Female Waveguide to Coax Adapter Operating From 12.4 GHz to 18 GHz, Ku Band PEWCA1023

URL: https://www.pasternack.com/wr-62-ug1665-square-sma-female-waveguide-coax-adapter-pewca1023-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451 Sales@Pasternack.com • Techsupport@Pasternack.com

© 2018 Pasternack Enterprises All Rights Reserved



PEWCA1023

PEWCA1023 CAD Drawing

WR-62 UG-1665/U Square Cover Flange to SMA Female Waveguide to Coax Adapter Operating From 12.4 GHz to 18 GHz, Ku Band

