



## **RF Cable Assemblies Technical Data Sheet**

#### Configuration

- Connector 1: N Male
- Connector 2: N Male
- Cable Type: RG225

#### Features

- Max Frequency 400 MHz
- Double Shielded
- PTFE (FG) Jacket

### Applications

General Purpose

Laboratory Use

#### Description

Pasternack's PE33269-36 type N male to type N male 36 inch cable using RG225 coax is part of our full line of RF components available for same-day shipping. Pasternack's flexible RF cable assemblies are ideal for applications where tight bends and flexure are required. This Pasternack type N to type N cable assembly has a male to male gender configuration with 50 ohm flexible RG225 coax. The PE33269-36 type N male to type N male cable assembly operates to 400 MHz. The double shielding of this Pasternack cable assembly provides excellent shielding effectiveness.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other available RF cable assembly value added services include connector orientation or clocking, heat shrink booting and custom labeling. RF testing can also be performed to document the electrical performance of your cable assembly.

#### **Electrical Specifications**

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		400	MHz
VSWR			1.4:1	
Capacitance		32.4 [106.3]		pF/ft [pF/m]

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: N Male to N Male Cable 36 Inch Length Using RG225 Coax PE33269-36

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com

#### PE33269-36



## **RF Cable Assemblies Technical Data Sheet**

Specifications by Frequency



## PE33269-36

Description	F1	F2	F3	F4	F5	Units
Frequency	50	100	250	500	1,000	MHz
Insertion Loss (Typ.)	0.219	0.238	0.294			dB
VSWR (Max.)	1.4:1	1.4:1	1.4:1	1.4:1	1.4:1	
Return Loss (Max.)	15.56	15.563	15.563	15.563	15.563	dB

#### **Mechanical Specifications**

Cable Assembly Length\* Diameter

Weight

#### Cable

Cable Type Impedance Inner Conductor Type Inner Conductor Material and Plating Dielectric Type Number of Shields Shield Layer 1 Shield Layer 2 Jacket Material Jacket Diameter 36 in [914.4 mm] 0.79 in [20.07 mm] 0.731 lbs [331.58 g]

RG225 50 Ohms Stranded Copper, Silver PTFE 2 Silver Plated Copper Braid Silver Plated Copper Braid PTFE (FG), Tan 0.43 in [10.92 mm]

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: N Male to N Male Cable 36 Inch Length Using RG225 Coax PE33269-36

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451 Sales@Pasternack.com • Techsupport@Pasternack.com



## **RF Cable Assemblies Technical Data Sheet**

## PE33269-36

#### Connectors

Description	Connector 1	Connector 2	
Туре	N Male	N Male	
Specification	MIL-STD-348A	MIL-STD-348A	
Impedance	50 Ohms	50 Ohms	
Contact Material and Plating	Brass, Gold	Brass, Gold	
Contact Plating Specification	30µ in. minimum	30µ in. minimum	
Dielectric Type	Teflon	Teflon	
Body Material and Plating	Brass, Nickel	Brass, Nickel	
Body Plating Specification	100µ in. minimum	100µ in. minimum	
Coupling Nut Material and Plating	Brass, Nickel	Brass, Nickel	
Coupling Nut Plating Specification	100µ in. minimum	100µ in. minimum	

Mechanical Specification Notes:

\*All cable assemblies have a length tolerance of 1.5% or ± 3/8", whichever is greater.

**Compliance Certifications** (see product page for current document)

#### **Plotted and Other Data**

Notes:

• Values at 25°C, sea level.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: N Male to N Male Cable 36 Inch Length Using RG225 Coax PE33269-36

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451 Sales@Pasternack.com • Techsupport@Pasternack.com





## **RF Cable Assemblies Technical Data Sheet**

## PE33269-36

# How to Order PE33269 Part Number Configuration: - XX uu - Unit of Measure: cm = Centimeters <blank> = Inches Length Base Number Example: PE33269-12 = 12 inches long cable PE33269-100cm = 100 cm long cable N Male to N Male Cable 36 Inch Length Using RG225 Coax from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry. Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: N Male to N Male Cable 36 Inch Length Using RG225 Coax PE33269-36 URL: https://www.pasternack.com/n-male-n-male-rg225u-cable-assembly-pe33269-36-p.aspx The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451 Sales@Pasternack.com • Techsupport@Pasternack.com

© 2019 Pasternack Enterprises All Rights Reserved

PE33269-36 CAD Drawing N Male to N Male Cable 36 Inch Length Using RG225 Coax

