


















| COMPONENTS | IMPEDANCE |
|------------|-----------|
| FAKRA JACK | 50 OHM |
| FAKRA PLUG | 50 OHM |
| PE-C100 | 50 OHM |
| | |

| Standard Lengths | |
|------------------|-------------------------|
| -12 | 12" |
| -24 | 24" |
| -36 | 36" |
| -48 | 48" |
| -60 | 60" |
| -XXX | Custom Length in Inches |
| | |

Part Configurator

1. Replace Y with code.
2. Replace XX with length in inches.

| CODING | JACK | PLUG | COLOR | APPLICATION |
|--------|---|---|------------|--|
| A |  |  | BLACK | RADIO WITH PHANTOM SUPPLY |
| B |  |  | WHITE | RADIO WITHOUT PHANTOM SUPPLY |
| C |  |  | BLUE | GPS: TELEMATICS OR NAVIGATION |
| D |  |  | BORDEAUX | GSM: CELLULAR PHONE |
| H |  |  | VIOLET | GPS: TELEMATICS AND NAVIGATION |
| I |  |  | BEIGE | BLUETOOTH |
| K |  |  | CURRY | RADIO WITH IF OUTPUT (ANTENNA DIVERSITY) |
| Z |  |  | WATER BLUE | NEUTRAL CODING |



* PE-C Series is a functionally equivalent to Times Microwave LMR[®] series

** LMR[®] is a registered trademark of Times Microwave



PASTERNAK ENTERPRISES, INC.
P.O BOX 16759, IRVINE, CA 92623
PHONE (949) 261-1920 FAX (949) 261-7451
WEB ADDRESS: www.pasternack.com
E-MAIL ADDRESS: sales@pasternack.com
COAXIAL & FIBER OPTICS

| | | | | | |
|--------------------|----------------|--|-----------|--------|-----|
| DWG TITLE | | DES. | | | |
| PE38748Y-XX | | FAKRA JACK TO FAKRA PLUG, PE-C100 COAX | | | |
| REV. - | FSCM NO. 53919 | CAD FILE 021508 | SCALE N/A | SIZE A | 127 |

- NOTES:**
1. UNLESS OTHERWISE SPECIFIED ALL DIMENSIONS ARE NOMINAL.
 2. ALL SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE AT ANY TIME.
 3. DIMENSIONS ARE IN INCHES.
 4. LENGTH TOLERANCE IS ± 1.5% OR 3/8", WHICHEVER IS GREATER.