



# **RF Cable Assemblies Technical Data Sheet**

### PE3W05737LF/HS


# Configuration

Connector 1: SSMB Jack BulkheadConnector 2: SMA Male Right Angle

Cable Type: LMR-100A

## **Features**

- Max Frequency 3 GHz
- Shielding Effectivity > 90 dB
- 66% Phase Velocity
- · Double Shielded
- PVC Jacket



# **Applications**

· General Purpose

· Laboratory Use

#### Description

Pasternack's PE3W05737LF/HS SSMB jack bulkhead to SMA male right angle cable using LMR-100 coax is part of our full line of RF components available for same-day shipping. Pasternack's flexible RF cable assemblies are ideal for applications where tight bends and flexure are required. This Pasternack SSMB to SMA cable assembly has a jack to male gender configuration with 50 ohm flexible LMR-100A coax. The PE3W05737LF/HS SSMB jack to SMA male cable assembly operates to 3 GHz. The right angle SMA interface on the LMR-100A cable allows for easier connections in tight spaces. Our RF cable assembly with SSMB bulkhead interface allows designers to create external connections on their product enclosures, and can be used in a variety of other rack mount and panel mount applications. The double shielding of this Pasternack cable assembly provides excellent shielding effectiveness of better than 90 dB.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other available RF cable assembly value added services include connector orientation or clocking, heat shrink booting and custom labeling. RF testing can also be performed to document the electrical performance of your cable assembly.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: SSMB Jack Bulkhead to SMA Male Right Angle Cable Using LMR-100 Coax with HeatShrink, LF Solder PE3W05737LF/HS

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com





### RF Cable Assemblies Technical Data Sheet

# **PE3W05737LF/HS**

### **Electrical Specifications**

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		3	GHz
VSWR		735	1.5:1	
Velocity of Propagation		66		%
RF Shielding	90			dB
Group Delay		1.54 [5.05]		ns/ft [ns/m]
Capacitance		30.8 [101.05]		pF/ft [pF/m]
Inductance		0.077 [0.25]		uH/ft [uH/m]
DC Resistance Inner Conductor		81 [265.75]		Ohms/1000ft [Ohms/
Km]				
DC Resistance Outer Conductor		9.5 [31.17]		Ohms/1000ft [Ohms/
Km]				
Jacket Spark			2,000	Vrms

#### **Specifications by Frequency**

Description	F1	F2	F3	F4	F5	Units
Frequency	0.25	0.5	1	2.5	3	GHz
Insertion Loss (Max.)	0.12 0.39	0.17 0.56	0.24 0.79	0.4 1.31	0.44 1.44	dB/ft dB/m

**Electrical Specification Notes:** 

Insertion Loss does not include the loss of connectors. Insertion Loss is estimated as 0.3dB of connector loss.

# **Mechanical Specifications**

#### **Cable Assembly**

Diameter 0.315 in [8 mm]

#### Cable

Cable TypeLMR-100AImpedance50 OhmsInner Conductor TypeSolid

Inner Conductor Material and Plating Copper Clad Steel

Dielectric Type PE
Number of Shields 2

Shield Layer 1 Aluminum Tape
Shield Layer 2 Tinned Copper Braid

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: SSMB Jack Bulkhead to SMA Male Right Angle Cable Using LMR-100 Coax with HeatShrink, LF Solder PE3W05737LF/HS

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com





# **RF Cable Assemblies Technical Data Sheet**

# **PE3W05737LF/HS**

Jacket MaterialPVC, BlackJacket Diameter0.11 in [2.79 mm]

One Time Minimum Bend Radius

Repeated Minimum Bend Radius

Bending Moment

Flat Plate Crush

Tensile Strength

0.25 in [6.35 mm]

1 in [25.4 mm]

0.1 lbs-ft [0.14 N-m]

10 lbs/in [0.18 Kg/mm]

15 lbs [6.8 Kg]

#### Connectors

Connector 1	Connector 2		
SSMB Jack Bulkhead	SMA Male Right Angle		
MIL-STD-348	MIL-STD-348A		
50 Ohms	50 Ohms		
Gold	Brass, Gold		
MIL-G-45204	50 μin minimum		
PTFE	PTFE		
Brass, Gold	Brass, Nickel		
MIL-G-45204	100 µin minimum		
Brass, Nickel			
	100 µin minimum		
	5/16 inch		
	3 in-lbs [0.34 Nm]		
	SSMB Jack Bulkhead  MIL-STD-348  50 Ohms  Gold  MIL-G-45204  PTFE  Brass, Gold		

Mechanical Specification Notes:

Compliance Certifications (see product page for current document)

#### **Plotted and Other Data**

Notes:

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: SSMB Jack Bulkhead to SMA Male Right Angle Cable Using LMR-100 Coax with HeatShrink, LF Solder PE3W05737LF/HS

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com

<sup>\*</sup>All cable assemblies have a length tolerance of 1.5% or ± 3/8", whichever is greater.





### RF Cable Assemblies Technical Data Sheet

# **PE3W05737LF/HS**

#### **How to Order**

Part Number Configuration:

PE3W05737LF/HS - xx uu

Unit of Measure:
cm = Centimeters
<br/>
<br/>
<br/>
<br/>
Length
Base Number

Example: PE3W05737LF/HS-12 = 12 inches long cable PE3W05737LF/HS-100cm = 100 cm long cable

SSMB Jack Bulkhead to SMA Male Right Angle Cable Using LMR-100 Coax with HeatShrink, LF Solder from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: SSMB Jack Bulkhead to SMA Male Right Angle Cable Using LMR-100 Coax with HeatShrink, LF Solder PE3W05737LF/HS

URL: https://www.pasternack.com/ssmb-jack-sma-male-lmr100-cable-assembly-pe3w05737lf-hs-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451

**PE3W05737LF/HS CAD Drawing** SSMB Jack Bulkhead to SMA Male Right Angle Cable Using LMR-100 Coax with HeatShrink, LF Solder

