

## BNC Twinax Plug to BNC Twinax Jack Right Angle Adapter



## **RF Adapters Technical Data Sheet**

# PE9377

### Configuration

- BNC Twinax Plug Connector 1
- BNC Twinax Jack Connector 2

#### Features

- BNC Twinax Interface compliant with MIL-STD-348
- Silver Plated Contact

#### **Applications**

General Purpose Test

- •78 Ohms
- Right Angle Body Geometry
- Contact Plating per QQ-S-365

#### Description

Pasternack's PE9377 BNC Twinax plug to BNC Twinax jack right angle adapter is part of our full line of RF components available for same-day shipping. Our BNC Twinax to BNC Twinax adapter has a plug to jack gender configuration. This low profile right angle BNC Twinax adapter allows for easier connections in tight spaces.

RF adapters are often used to enable connections between two connector types that would otherwise not mate. Certain adapter configurations can also be used to protect connectors on expensive equipment where the number of connect/ disconnect cycles is high. An RF, microwave or millimeter wave adapter is connected to the equipment, and the commonly changed connection is made with the adapter which can be easily replaced when it wears out after high usage; such adapters are referred to as connector savers. Pasternack also offers bulkhead, panel mount, hermetically sealed, reverse polarity, and isolated ground adapter varieties to serve all of your RF, microwave and millimeter wave needs.

#### **Mechanical Specifications**

Size	
Length	1.02 in [25.91 mm]
Width	0.57 in [14.48 mm]
Height	0.89 in [22.61 mm]
Weight	0.034 lbs [15.42 g]
-	

Description	Connector 1	Connector 2
Туре	BNC Twinax Plug	BNC Twinax Jack
Polarity	Standard	Standard
Interface Specification	MIL-STD-348	MIL-STD-348

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: BNC Twinax Plug to BNC Twinax Jack Right Angle Adapter PE9377

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com

ISO 9001 : 2008 Registered





# BNC Twinax Plug to BNC Twinax Jack Right Angle Adapter



# **RF Adapters Technical Data Sheet**

## **PE9377**

#### Material Specifications

Connector 1		Connector 2		
Material	Plating	Material	Plating	
BNC Twinax Plug	BNC Twinax Jack			
	Silver		Silver	
	QQ-S-365		QQ-S-365	
PTFE		PTFE		
		Brass	Nickel	
			QQ-N-290	
Brass	Nickel			
	QQ-N-290			
Brass	Nickel			
	QQ-N-290			
	Material BNC Twinax Plug PTFE Brass	MaterialPlatingBNC Twinax PlugSilverQQ-S-365QQ-S-365PTFEImage: Comparison of the sector of t	MaterialPlatingMaterialBNC Twinax PlugBNC Twinax JackSilver QQ-S-365QQ-S-365PTFEPTFEBrassBrassBrassNickel QQ-N-290BrassNickel	

#### Compliance Certifications (see product page for current document)

BNC Twinax Plug to BNC Twinax Jack Right Angle Adapter from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: BNC Twinax Plug to BNC Twinax Jack Right Angle Adapter PE9377

URL: https://www.pasternack.com/bnc-twinax-plug-bnc-twinax-jack-right-angle-adapter-pe9377-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451 Sales@Pasternack.com • Techsupport@Pasternack.com



**PE9377 CAD Drawing** BNC Twinax Plug to BNC Twinax Jack Right Angle Adapter

