



WR-102 UG-1493/U Square Cover Flange to N Male Waveguide to Coax Adapter Operating from 7 GHz to 11 GHz

Waveguide to Coax Adapters Technical Data Sheet

PEWCA1039

Features

- 7 to 11 GHz Frequency Range
- WR-102 Waveguide Interface
- UG-1493/U Square Cover Flange
- N Male RF Interface
- Right Angle

Applications

- Test Benches
- Radar
- Satellite
- Microwave Radio Systems
- Military and Space
- Communication Systems

Description

The PEWCA1039 is a waveguide to coaxial adapter operating in the Band with a 7 to 11 GHz frequency range. This adapter offers a WR-102 waveguide interface size using a standard UG-1493/U Square Cover Flange. The PEWCA1039 is constructed of Aluminum Alloy and painted to ensure durability. The coaxial connector offered by this adapter uses a N Male Connector. All waveguide components available for same day shipping.

Configuration

Waveguide Size	WR-102
Flange	UG-1493/U Square Cover
RF Connector	N Male
Impedance	50 Ohms
Body Geometry	Right Angle

Electrical Specifications

Description	Minimum	Typical	Maximum	Units
Frequency Range	7		11	GHz
VSWR		1.25:1		

Mechanical Specifications

RF Connector	
Connector Type	N Male
Waveguide Interface	
Waveguide Type	WR-102
Flange Type	Square Cover
Flange Designation	UG-1493/U
Body Material and Plating	Aluminum, Paint

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [WR-102 UG-1493/U Square Cover Flange to N Male Waveguide to Coax Adapter Operating from 7 GHz to 11 GHz PEWCA1039](#)



WR-102 UG-1493/U Square Cover Flange to N Male
Waveguide to Coax Adapter Operating from 7 GHz to 11 GHz

Waveguide to Coax Adapters Technical Data Sheet

PEWCA1039


Compliance Certifications (see [product page](#) for current document)

Plotted and Other Data

Notes:

- Values at +25 °C, sea level unless stated otherwise

Typical Performance Data



WR-102 UG-1493/U Square Cover Flange to N Male Waveguide to Coax Adapter Operating from 7 GHz to 11 GHz from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry.




Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [WR-102 UG-1493/U Square Cover Flange to N Male Waveguide to Coax Adapter Operating from 7 GHz to 11 GHz PEWCA1039](#)

URL: <https://www.pasternack.com/wr102-ug1493-square-flange-to-type-n-male-waveguide-coax-adapter-11ghz-pewca1039-p.aspx>

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

PEWCA1039 CAD Drawing

WR-102 UG-1493/U Square Cover Flange to N Male Waveguide to Coax Adapter Operating from 7 GHz to 11 GHz



STANDARD TOLERANCES

.X ±0.2
.XX ±0.01
.XXX ±0.005

*STANDARD TOLERANCES APPLY ONLY TO DIMENSIONS IN INCHES



Pasternack Enterprises, Inc.
P.O. Box 16759 | Irvine | CA | 92623
Phone: (949) 261-1920 | Fax: (949) 261-7451
Website: www.pasternack.com | E-Mail: sales@pasternack.com

DWG TITLE

PEWCA1039

NOTES:
1. UNLESS OTHERWISE SPECIFIED ALL DIMENSIONS ARE NOMINAL.
2. ALL SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE AT ANY TIME.
3. DIMENSIONS ARE IN INCHES [mm].

CAGE CODE 53919

CAD FILE 10/15/18

SCALE N/A

SIZE A

7361