

# WR-112 UG-138/U Square Cover Flange to SMA Female Waveguide to Coax Adapter, 7.05 GHz to 10 GHz, H Band, Aluminum, Paint



### Waveguide to Coax Adapters Technical Data Sheet

PEWCA1040

#### **Features**

- H Band
- 7.05 to 10 GHz Frequency Range
- WR-112 Waveguide Interface

- UG-138/U Square Cover Flange
- SMA Female RF Interface
- Right Angle

#### **Applications**

- Test Benches
- Radar

- Satellite
- Microwave Radio Systems
- Military and Space
- Communication Systems

#### **Description**

The PEWCA1040 is a waveguide to coaxial adapter operating in the H Band with a 7.05 to 10 GHz frequency range. This adapter offers a WR-112 waveguide interface size using a standard UG-138/U Square Cover Flange. The PEWCA1040 is constructed of Aluminum Alloy and painted to ensure durability. The coaxial connector offered by this adapter uses a SMA Female Connector.

#### Configuration

Waveguide Size

Flange

RF Connector

Impedance

**Body Geometry** 

WR-112

UG-138/U Square Cover

**SMA Female** 

50 Ohms

Right Angle

#### **Electrical Specifications**

Description	Minimum	Typical	Maximum	Units
Frequency Range	7.05		10	GHz
VSWR		1.25:1		

#### **Mechanical Specifications**

**RF Connector** 

Connector Type SMA Female

Waveguide Interface

Waveguide Type WR-112
Flange Type Square Cover
Flange Designation UG-138/U
Body Material and Plating Aluminum, Paint

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: WR-112 UG-138/U Square Cover Flange to SMA Female Waveguide to Coax Adapter, 7.05 GHz to 10 GHz, H Band, Aluminum, Paint PEWCA1040

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com



WR-112 UG-138/U Square Cover Flange to SMA Female Waveguide to Coax Adapter, 7.05 GHz to 10 GHz, H Band, Aluminum, Paint



## Waveguide to Coax Adapters Technical Data Sheet

PEWCA1040


Compliance Certifications (see product page for current document)

#### **Plotted and Other Data**

Notes:

• Values at +25 °C, sea level unless stated otherwise

#### **Typical Performance Data**



WR-112 UG-138/U Square Cover Flange to SMA Female Waveguide to Coax Adapter, 7.05 GHz to 10 GHz, H Band, Aluminum, Paint from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: WR-112 UG-138/U Square Cover Flange to SMA Female Waveguide to Coax Adapter, 7.05 GHz to 10 GHz, H Band, Aluminum, Paint PEWCA1040

URL: https://www.pasternack.com/wr112-ug138-square-flange-to-sma-female-waveguide-coax-adapter-10-ghz-pewca1040-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451

# **PEWCA1040 CAD Drawing**

WR-112 UG-138/U Square Cover Flange to SMA Female Waveguide to Coax Adapter, 7.05 GHz to 10 GHz, H Band, Aluminum, Paint

